

Gossiping with interference in radio chain networks

Jean-Claude Bermond

Université Côte d'Azur, CNRS, Inria, I3S, France,
jean-claude.bermond@inria.fr

Takako Kodate

Department of Information and Sciences,
Tokyo Woman's Christian University, Japan,
kodate@lab.twcu.ac.jp

Joseph Yu

Department of Mathematics,
University of the Fraser Valley, B.C., Canada,
joseph.yu@ufv.ca

In this paper, we study the problem of gossiping with interference constraint in radio chain networks. Gossiping (or total exchange information) is a protocol where each node in the network has a message and wants to distribute its own message to every other node in the network. The gossiping problem consists in finding the minimum running time (makespan) of a gossiping protocol and efficient algorithms that attain this makespan.

Transmission model The radio chain network is modeled as a symmetric dipath P_n , where the vertices represent the nodes and the arcs represent the possible communications. A call (s, r) is defined as the transmission from the node s to the node r , in which s is the *sender* and r is the *receiver* and (s, r) is an arc of the dipath. The network is assumed to be synchronous and the time is slotted into *steps*. We suppose that each device is equipped with a half duplex interface; so, a node cannot both receive and transmit during a step.

Interference model Furthermore, communication is subject to interference constraints. We use a binary asymmetric model of interference based on the distance in the communication digraph like the ones used in [1, 2, 6]. Let $d(s, r)$ denote the distance, that is the length of a shortest directed path, from s to r in P_n and d_I be a non negative integer. We assume that when a node s transmits, all nodes v such that $d(s, v) \leq d_I$ are subject to the interference from s transmission. So two calls (s, r) and (s', r') do not interfere if $d(s, r') > d_I$ and $d(s', r) > d_I$. During a given step only non interfering (or compatible) calls can be done and we will define a round as a set of such compatible calls. We focus here on the case where $d_I = 1$.

Main result This problem has been studied in general in [5] where approximation results are given (see also the survey [4]). In [3] we solved completely the gossiping problem in radio ring networks within this model. Here we determine exactly the minimum number of rounds R needed to achieve a gossiping when transmission network is a dipath P_n on n nodes and the interference distance is $d_I = 1$. We first prove the lower bound and then give gossiping algorithms which meet this lower bound.

Theorem 1 *The minimum number of rounds R needed to achieve a gossiping in a chain network P_n ($n \geq 3$), with the interference model $d_I = 1$ is :*

$$R = \begin{cases} 3n - 5 & n \geq 4 \\ 5 & n = 3 \end{cases}$$

References

- [1] J.C. Bermond, R. Correa and M.L. Yu.: Optimal gathering protocols on paths under interference constraints, *Discrete Mathematics* 309: 5574–5587, 2009.
- [2] J.-C. Bermond, J. Galtier, R. Klasing, N. Morales, and S. Pérennes. Hardness and approximation of gathering in static radio networks. *Parallel Processing Letters*, 16(2): 165–183, 2006.
- [3] J.C. Bermond, T. Kodate and M.L. Yu.: Gossiping with interferences in radio ring networks presented at *JCDCG³* 2017, full version submitted to Graphs and Combinatorics
- [4] L. Gasieniec. On efficient gossiping in radio networks. Proc. Int. Conference on Theoretical Computer Science Colloquium on structural information and communication complexity, SIROCCO 2009, Lectures Notes in Computer science, springer Verlag, vol 5869: 2–14, 2010.
- [5] L. Gasieniec and I. Potapov. Gossiping with unit messages in known radio networks. Proc. 2nd IFIP Int. Conference on Theoretical Computer Science: 193–205, 2002.
- [6] R. Klasing, N. Morales, and S. Pérennes. On the complexity of bandwidth allocation in radio networks. *Theoretical Computer Science*, 406(3): 225–239, 2008.